

# D382 Combustible Gas Detector (Macurco GD-2A)

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ 12 VDC/VAC or 24 VDC/VAC operation
- ▶ Self-purging semiconductor sensor requires no maintenance or recalibration
- ▶ SPDT (Form C) alarm Relay and SPST (Form A) trouble relay designed for seamless connection to control panels or other devices
- ▶ Installer selectable self-restoring or latching functionality
- ▶ Red and Green LED status indicators

The D382 Combustible Gas Detector (Macurco GD-2A) detects the presence of combustible gases such as propane and natural gas (methane). It is rated by Underwriters Laboratories (UL) to alarm below 25% of the lower explosion level (LEL) of propane or methane.

Use in non-hazardous locations such as residences, retail stores, office buildings, and institutional buildings. It is usually installed in rooms where gas appliances are located or in rooms that are susceptible to gas seepage.



**Notice**

Do not use in industrial locations such as factories, refineries and chemical plants.



**Notice**

The D382 does **not** detect carbon monoxide.

## Functions

### Input Power

The detector uses a full-wave bridge rectifier so it is independent of input power polarity. It operates on AC or DC voltages from 12 V to 24V. A switching regulator is used to efficiently match the wide input voltage range to the fixed internal power system.

### Status LEDs

The detector has one green and one red status LED on the front of the detector.

The detector has an internal two-minute time delay that prevents alarms during the warm-up of the gas sensor. During the warm-up period, the green LED light flashes. Once the delay is over, the continuous green light indicates normal operation.

The detector has a supervisory circuit of critical functions. A trouble condition, due to a failure of a non-reliable component, results in both lights flashing and the trouble relay activating. A power failure also causes the trouble relay to activate.

The red LED turns on at the same time the alarm relay activates to indicate the alarm condition.

## Certifications and approvals

3M (Macurco) holds the following Listings and Approvals:

Region	Certification
USA	UL FTAM: Gas and Vapor Detectors and Sensors (UL2075)

## Installation/configuration notes

### Compatibility Information

The combustible gas detector is compatible with all UL Listed control panels that have four-wire power and alarm initiating circuits.

### Mounting Considerations

The detector is capable of supervising an area of up to 900 ft<sup>2</sup> (83.6 m<sup>2</sup>). In larger areas, space the detectors on 30 ft (10 m) centers.

Natural gas (methane) is lighter than air and collects at the ceiling. Bottle gas (propane) is heavier than air and collects on the floor. Mount the detector 1 ft. (0.3 m) from the floor, or 1 ft. (0.3 m) from the ceiling, depending on the targeted gas. Mount the detector at least 6 in. (15.2 cm) from corners to avoid dead air space.

The detector mounts on a standard four-inch square back box or a double-gang box.

### Wiring Considerations

The combustible gas detector must be installed on a separate circuit or zone reserved for combustible gas detectors and cannot be combined with smoke, heat, or intrusion detectors. Alarms for this circuit or zone must activate audible notification appliances of at least 85 dB with a distinctive sound for gas detection. Use the indicated wire size for the detector loop:

Length of Wire Run	Recommended Wire Size
200 ft (61 m) or less	22 AWG (0.8 mm)
Up to 575 ft (175 m)	20 AWG (1.0 mm)
Up to 686 ft (209 m)	18 AWG (1.2 mm)
Up to 1300 ft (396 m)	16 AWG (1.5 mm)
Up to 2100 ft (640 m)	14 AWG (1.8 mm)
Up to 3200 ft (975 m)	12 AWG (2.3 mm)

## Parts included

Quant.	Component
1	Combustible gas detector
1	Hardware pack
1	Literature pack

## Technical specifications

### Environmental Considerations

Temperature (operating):	+32°F to +120°F (0°C to +49°C); For UL installations, +40°F to +120°F (+4.4°C to +49°C)
--------------------------	---

### Mechanical Properties

Color:	White
Dimensions (H x W x D):	4.5 in. x 5.0 in. x 1.625 in. (11.4 cm x 12.7 cm x 4.1 cm)
Weight (shipping):	0.54 lb (0.25 kg)

### Outputs

#### Alarm

Relay Configuration:	one SPDT (Form C)
Relay Rating:	0.125 A, 40 V, 3 VA
Set Point:	25% below LEL for propane or methane

#### Trouble

Relay Configuration:	one SPST (Form A)
Relay Rating:	0.25 A, 40 v, 10 VA

### Power Requirements

#### Current

Alarm:	At 12 VDC: 70 mA; at 24 VDC: 35 mA At 12 VAC: 100 mA; at 24 VAC: 65 mA
Standby:	At 12 VDC: 45 mA; at 24 VDC: 22 mA At 12 VAC: 65 mA; at 24 VAC: 45 mA

#### Voltage

VDC input:	12 VDC to 24 VDC
VAC input:	12 VAC to 24 VAC, 50 Hz or 60 Hz

### Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

3M and Macurco are trademarks of 3M.

## Ordering information

### D382 Combustible Gas Detector (Macurco GD-2A)

The D382 is installed in rooms where gas appliances are located or rooms susceptible to gas seepage where it detects the presence of combustible gases such as propane and methane. It is compatible with all UL Listed control panels with four-wire power and alarm initiating circuits.

Order number **D382**

---

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com